

LT9211 --- Product Brief

MIPI/TTL/2-Port LVDS to MIPI/TTL/2-Port LVDS Converter

Features

Dual-Port LVDS Transmitter

- Compatible with VESA and JEIDA standard
- 1~2 Configurable Port
- Two Port Simultaneous Display Supported
- Up to 1080P 60Hz
- Support DE Mode
- Data Port , Data Lane and Polarity Swapping
- Programmable Pre-emphasis
- Support output SSC(30KHz± 5%)

MIPI Transmitter

- Compliant with DCS1.02, D-PHY1.2 ,DSI1.2 and CSI-2 1.00
- 1 Clock Lane and 1~4 Configurable Data Lanes
- Two Port Simultaneous Display Supported
- Up to 1.8Gb/s per Data Lane
- Resolution Up to 2560x1440 60Hz
- Data Lane and Polarity Swapping
- Both Non-Burst and Burst Video Mode Supported
- Support RGB666, Loosely RGB666, RGB888, RGB565, 16-bit YCbCr4:2:2, 24-bit YCbCr 4:2:2 Video Format

TTL Output

- Support 24-bit RGB and BT656/BT1120
- Both DDR and SDR sampling supported
- Support both 1.8V and 3.3V Voltage Output
- Resolution up to 2560x1440 60Hz

Dual-Port LVDS Receiver

- Compatible with VESA and JEIDA standard
- 1~2 Configurable Port
- Up to 1080P 60Hz
- Support DE Mode

- Data Port ,Data Lane and Polarity Swapping
- Internal Rterm Calibration with Less than 5% Error
- Programmable Equalization
- Support input Dessc(30KHz± 5%)

TTL Input

- Support 24-bit RGB and BT656/BT1120
- Both DDR and SDR sampling supported
- Support SYNC Mode and DE Mode
- Support both 1.8V and 3.3V Input Voltage
- Resolution up to 2560x1440 60Hz

Single-Port MIPI Receiver

- Compliant with DCS1.02, D-PHY1.2 ,DSI1.2 and CSI-2 1.00
- 1 Clock Lane and 1~4 Configurable Data Lanes
- Two Port Input switchable
- Up to 1.8Gb/s per Data Lane
- Resolution Up to 2560x1440 60Hz
- Data Lane and Polarity Swapping
- Both Non-Burst and Burst Video Mode Supported
- Support RGB666, Loosely RGB666, RGB888, RGB565, 16-bit YCbCr4:2:2, 24-bit YCbCr 4:2:2 Video Format

Miscellaneous

- 1.8V and 3.3V Power Supply
- Alternative Input and Output configuration for LVDS/TTL/MIPI
- MIPI/LVDS muxer and splitter supported
- MIPI-LVDS Levelshifter for FPGA
- Support 100KHz and 400KHz I2C Slave
- External 25MHz 200ppm Crystal Reference Clock is Preferred
- Temperature Range: -40°C ~ +85°C
- Packaged in QFN64 7.5mm x 7.5mm

Description

The Lontium LT9211 is a high performance convertor which interconvertible between MIPI DSI/CSI-2/Dual-Port LVDS and TTL except for 24bit TTL to 24bit TTL with both SYNC and DE. The LT9211 deserializes input MIPI/LVDS/TTL video data, decodes packets, and converts the formatted video data stream to MIPI/LVDS/TTL transmitter output between AP and mobile display panel or camera.

The LT9211 can be used as 2-Port MIPI/LVDS Repeater which support maximum 14dB input equalization and programmable pre-emphasis to improve performance.

The LT9211 can also be used as MIPI/LVDS Muxer and Splitter. For MIPI Repeater, Muxer and Splitter, we do not

LONTIUM CONFIDENTIAL

Copyright © 2018-2020 Lontium Semiconductor Corporation, All rights reserved.

Lontium Semiconductor Proprietary & Confidential

This document and the information it contains belong to Lontium Semiconductor. Any review, use, dissemination, distribution or copying of this document or its information outside the scope of a signed agreement with Lontium is strictly prohibited.

LONTIUM DISCLAIMS ALL WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING THOSE OF NONINFRINGEMENT, MERCHANTABILITY, TITLE AND FITNESS FOR A PARTICULAR PURPOSE. CUSTOMERS EXPRESSLY ASSUME THEIR OWN RISK IN RELYING ON THIS DOCUMENT.

LONTIUM PRODUCTS ARE NOT DESIGNED OR INTENDED FOR USE IN LIFE SUPPORT APPLIANCES, DEVICES OR SYSTEMS WHERE A MALFUNCTION OF A LONTIUM DEVICE COULD RESoPLIANCES, DEVICES OR SYST