

LT8918L --- Product Brief

Dual-Port LVDS to MIPI DSI/CSI-2 Bridge

Features

Single/Dual-Port LVDS Receiver

- Compatible with VESA and JEIDA standard
- 1~2 configurable port
- 1 clock lane and 1~5 data lanes per port
- Data lane and polarity swapping
- Support Maximum Data Rate 1.2Gb/s/lane
- Resolution up to 1080P 60Hz for dual-port mode
- Input color depth supports 6-bit, 8-bit and 10-bit
- Support input De-SSC (30kHz +/- 5%)

Single-Port MIPI DSI Transmitter

- Compliant with DCS1.02, D-PHY1.1 & DSI1.02
- 1 Clock Lane and 1~4 Configurable Data Lanes
- 80Mb/s~1.5Gb/s per Data Lane
- Resolution Up to 1080P 60Hz
- Data Lane and Polarity Swapping
- Both Non-Burst and Burst Video Mode Supported
- Command Mode through Lane-0 Supported
- Support RGB666, Loosely RGB666, RGB888, RGB565, 16-bit YCbCr4:2:2, 24-bit YCbCr 4:2:2 Video Format

Single-Port MIPI CSI-2 Transmitter

- Compliant with D-PHY1.1 & CSI-2 1.0
- 1 Clock Lane and 1~4 Configurable Data Lanes
- 80Mb/s~1.5Gb/s per Data Lane
- Resolution Up to 1080P 60Hz
- Data Lane and Polarity Swapping
- Support RGB565, RGB666, RGB888, 8-bit YUV422 Video Format

Miscellaneous

- 1.8V Single Supply Power
- Support 100KHz and 400KHz I2C slave

- External 25MHz Crystal Reference Clock
- Temperature Range: -40°C to +85°C
- Packaged in QFN64 7.5mm x 7.5mm and BGA81 5mm x 5mm.

Description

The Lontium LT8918L is a high performance Dual-Port LVDS to MIPI DSI/CSI-2 bridge chip between AP and mobile display panel or camera.

LT8918L can be configured as single-port or dual-port with optional De-SSC function. The bridge deserializes input LVDS data, decodes packets and converts the formatted video data stream to MIPI DSI/CSI-2 transmitter output.

For MIPI DSI/CSI-2 output, LT8918L features a single port MIPI DSI or CSI-2 transmitter with 1 high-speed clock lane and 1~4 configurable high-speed data lanes operating at maximum 1.5Gb/s/lane, which can support a total bandwidth of up to 6Gb/s. LT8918L supports both Non-Burst and Burst DSI video data transferring, as well as Command Mode through Lane-0.

The LT8918L is fabricated in advanced CMOS process and implemented in a small outline 7.5mm x 7.5mm QFN64 package. This package is RoHS compliant and specified to operate from -40°C to +85°C.

Applications

- Mobile systems
- Cellular handsets
- Digital video cameras
- Digital still cameras
- Tablet PC, Notebook PC
- Car Display and Camera System

LONTIUM CONFETI

Copyright © 2016-2017 Lontium Semiconductor Corporation, All rights reserved.

Lontium Semiconductor Proprietary & Confidential

This document and the information it contains belong to Lontium Semiconductor. Any review, use, dissemination, distribution or copying of this document or its information outside the scope of a signed agreement with Lontium is strictly prohibited.

LONTIUM DISCLAIMS ALL WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING THOSE OF NONINFRINGEMENT

LONTIUM CONFIDENTIAL